



LOCATION	SYMBOL	DESCRIPTION	LOCATION IN FRAME
1-9	ALARM (100V, 0.1 Amp)	EXTERNAL ALARM	EXTERNAL
8-5	BP	LOW PRESSURE SWITCH	CONDENSER
8-3	BPT	INJECTION CLUTCH	ROAD COMPRESSOR
1-5	BPV	INJECTION SOLENOID	EVAPORATOR
D-12	BTY	BATTERY	ENGINE COMPARTMENT
0-12	BR	BRIDGE	STANDBY PANEL
A-8	CC	CAB COMMAND	CAB
1-2	CFM	CONDENSER FAN MOTOR	CONDENSER
1-7	CLHS	ROAD ELECTROMAGNETIC CLUTCH	ENGINE COMPARTMENT
J-12	CR	STANDBY ELECTROMAGNETIC CLUTCH	CONDENSER
N-12	CLHS	CLUTCH RELAY	STANDBY PANEL
B-2	C1	SMOOTHING CAPACITOR	EVAPORATOR
1-3	EPH1	EVAP FAN MOTOR 1	STANDBY PANEL
D-11	F1	FUSE 1	STANDBY PANEL
M-10	F2	FUSE 2	STANDBY PANEL
K-11	F3	FUSE 3	STANDBY PANEL
0-10	F4	230V PRIMARY TRANSFORMER FUSE 4	STANDBY PANEL
N-10	F5	400V PRIMARY TRANSFORMER FUSE 5	STANDBY PANEL
B-4	HP1	SECURITY SWITCH PRESSURE HP1	STANDBY PANEL
8-4	HP2	REGULATION PRESSURE SWITCH FOR FAN CONDENSER	STANDBY PANEL
1-5	HGS1	HOT GAS SOLENOID DEFOST - HEATING	CONDENSER
M-5	MC	MOTOR CONTACTOR	STANDBY PANEL
N-5/K-5	OL	OVERLOAD PROTECTOR	STANDBY PANEL
D-3	PC	PROCESS CIRCUIT	CONTROL BOX
D-13	PMC	GROUND PANEL	CONTROL BOX
N-2	PSR	POWER SUPPLY RECTIFIABLE	EXTERNAL
M-12	R	DISCHARGE RESISTOR	STANDBY PANEL
B-6	RAS	RETURN AIR SENSOR	EVAPORATOR
D-10	RR	ROAD RELAY	PROCESS CIRCUIT
N-7	SMB	STANDBY MOTOR	CONDENSER
F-10	SR	STANDBY RELAY	PROCESS CIRCUIT
Q-11	TR	TRANSFORMER	CONDENSER



BLOCK 3		
	F1 - F2	F3
+BAT = +12V	30A	5A
+BAT = +24V	15A	3A

- NOTES :
- UNIT SHOWN "OFF" POSITION.
 - WIRE IDENTIFICATION SYSTEM:
COLOR: WHITE = GROUND CIRCUITS
RED = 40V CIRCUITS
GREEN = 40V CIRCUITS
RED = 40V CIRCUITS
GREEN = 40V CIRCUITS
 - ADDITIONAL SYSTEMS, EXAMPLE: HGS2-HPS2
INDICATES A WIRE BETWEEN FAN NO. 2 AND HIGH PRESSURE HP AND FAN NO. 2
- * INDICATES A WIRELESS SIGNAL POINT.
 P10 CONNECTION.
 LIGHT LINES INDICATES WIRE IN THE SYSTEM.
 NORMALLY CLOSED CONTACTS.
 NORMALLY OPEN CONTACTS.
 INDICATES CONNECTION.
 MULTIPLE PLUS CONNECTION NUMBER.
 JUNCTION.

STANDARD	
OPTION 1	OPTION 2
ALARM (100V, 0.1 Amp)	HEATING (100V, 0.1 Amp)
DATE : 11/09/98	N : 02-00000 REV : SH:1/1